

Type: ETS4-VS3 Article No.: 083094


Sales text ACC.CONTACTOR VS1,VS2,VS3



Input with integral suppressor circuit for overvoltage limitation

| Ordering information | | | |
|-------------------------------|------------|------|-------------|
| Rated operational current | | | |
| AC-15 240 V | <i>l</i> e | Α | 2 |
| AC-15 415 V | <i>l</i> e | Α | 2 |
| DC 220 V | <i>l</i> e | Α | 0.03 |
| Actuating voltage | Us | V DC | 24 |
| Actuating current | 1 | mA | 25 |
| For use with contactor relays | | | As required |

Contact sequence



Notes concerning the table header

Rated operational current DC:

Making and breaking conditions DC-13, time L/R 300ms

Notes concerning the product group

Contactor coils with rated operational current > 2 A must be actuated via the DILA mini contactor relay.

Rated operational current DC:


Making and breaking conditions DC-13, time L/R 300ms

| General | | | |
|--|------------|-------------------|---|
| Standards | | | IEC/EN 60947, VDE 0660, UL, CSA |
| Lifespan, mechanical | | | |
| DC operated | Operations | × 10 ⁶ | 30 |
| Maximum operating frequency | | | |
| DC operated | Operations | × 10 ⁶ | 72000 |
| Climatic proofing | | | Damp heat, constant, to IEC 60068–2–78; Damp heat, cyclic, to IEC 60068–2–30 |
| Ambient temperature | | | |
| Open | | °C | -2560 |
| Enclosed | | °C | -2545 |
| Mounting position | | | As required |
| Mechanical shock resistance (half–sinusoidal shock, 20 ms) | | | |
| N/O contact | | g | 10 |
| Protection type | | | IP20 |
| Protection against direct contact when actuated from front (IEC 536) | | | Finger– and back–of–hand proof |
| Weight | | kg | 0,09 |
| Terminal capacities | | | |
| Solid | | mm ² | $2 \times (0.75 - 2.5)$ |
| Flexible with ferrule | | mm ² | 1 × (0.75 – 2.5) 2 × (0.75 – 1.5) |
| Solid or stranded | | AWG | 16 – 14 |
| Terminal screw | | | M3.5 |
| Pozidriv screwdriver | | Size | 2 |
| Standard screwdriver | | mm | 0.8 × 5.5 1 × 6 |
| Max. tightening torque | | Nm | 1,2 |
| Contacts | | | |

| Datad impulse withstand valtage | 11 | V/ A C | 0000 |
|--|------------------------|-------------------|---|
| Rated impulse withstand voltage | U_{imp} | V AC | |
| Overvoltage category/pollution degree | | | III/2 |
| Rated insulation voltage | <i>U</i> i | V AC | |
| Rated operational voltage | <i>U</i> e | V AC | 440 |
| Rated operational current | | | |
| AC-15 | | | |
| 220/240 V | <i>l</i> e | Α | 2 |
| 380/415 V | <i>l</i> e | Α | 2 |
| DC-13 | | | |
| DC-13 L/R - 15 ms | | | |
| Contacts in series: | | | |
| 1 | 24 V | Α | 2,6 |
| 1 | 60 V | Α | 1 |
| 1 | 110 V | Α | 0,6 |
| 1 | 220 V | Α | 0,2 |
| DC-13 L/R - 50 ms | | | |
| Contacts in series: | | | |
| 1 | 24 V | Α | 2 |
| 1 | 60 V | Α | 0,6 |
| 1 | 110 V | Α | 0,08 |
| 1 | 220 V | Α | 0,08 |
| DC-13 L/R - 300 ms | | | , |
| Contacts in series: | | | |
| 1 | 24 V | Α | 0,6 |
| 1 | 60 V | Α | 0,2 |
| 1 | 110 V | Α | 0,08 |
| 1 | 220 V | Α | 0,03 |
| Control circuit reliability (at $U_e = 24 \text{ V}$ DC, $U_{min} = 17 \text{ V}$, $I_{min} = 5.4 \text{ mA}$) | Failure rate | | -8, < one failure at 100 million operations |
| Conventional thermal current | <i>I</i> _{th} | Α | 6 |
| Component lifespan | | | |
| AC-15 | | | |
| 230 V, I _e = 0.1 A | Operations | × 10 ⁶ | 7 |
| 230 V, I _e = 1.2 A | Operations | × 10 ⁶ | |
| Short-circuit rating without welding | | | |
| Short–circuit protection maximum fuse | | | |
| 500 V | | A fast | 1 |
| | | Aiasi | 4 |
| Magnet systems | | | |

| Voltage tolerance | | | |
|---|-------------------|------|--|
| DC operated | | | |
| | Pick-up | × Uc | 0,85 – 1,2 |
| Power consumption | | | |
| DC operated | Pull-in = sealing | W | 0,6 |
| Duty factor | | % DF | 100 |
| Switching times at 100 % <i>U</i> _c (approximate values) | | | |
| DC operated closing delay | | ms | 7 |
| DC operated, opening delay | | ms | 3 |
| Notes | | | |
| Notes | | | For rated operational current: Making and breaking conditions to DC-13, L/R constant as stated Max. fuses for short-circuit protection: Transparent overlay "Fuses" for time/current characteristics (please enquire) For pick-up voltage, DC operated:Pure DC, AC bridge rectifier or smoothed double-wave rectification. For connection cross section: only use equal cross-sections |

Dimensions



Moeller GmbH, Hein-Moeller-Str. 7-11, D-53115 Bonn E-Mail: catalog@moeller.net, Internet: www.moeller.net, http://catalog.moeller.net HPL-C2007G V2.1 © 2007 by Moeller GmbH